

# Transformer Accessories

## Terminal Lug Kits

Catalog Number	KVA Sizes	Terminal Lug Quantity	Lug Cable Range	Quantity Cables Per Lug	Hardware	Approximate Weight in Pounds
					Quantity - Bolt Size	
50400	15 - 25 (1Ø) 15-25-30-37-1/2 (3Ø)	7	#14 - 1/0	1	(7) - 1/4 - 20 x 1"	1
50401	37 1/2 - 50 (1Ø) 45-50-60-75 (3Ø)	3	#14 - 1/0	1	(3) - 1/4 - 20 x 1"	3
		7	#6 - 250MCM	1	(7) - 5/16 - 18 x 1 1/2"	
50402	75-100 (1Ø) 100-112-150 (3Ø)	6	#6 - 350MCM	2	(6) - 1/2 - 13 x 2"	6
		6	#6 - 350MCM	1	(3) - 5/16 - 18 x 1 1/2" (6) - 3/8 - 16 x 1 1/2"	
50403*	225 (3Ø)	3	#4 - 500MCM	1	(3) - 3/8 - 16 x 1 1/2"	6
		4	#2 - 600MCM	2	(4) - 1/2 - 13 x 2"	
50404*	300 (3Ø)	3	#6 - 350MCM	2	(3) - 1/2 - 13 x 2"	8
		12	#4 - 500MCM	1	(9) - 3/8 - 16 x 2"	
50405*	400-500 (3Ø)	16	300-800MCM	1	(13) - 1/2 - 13 x 2 1/2"	15
		3	#2 - 600MCM	2		

### Notes:

1. Primary and secondary lug kits included with transformers rated 15 KVA - 75 KVA, 150° C rise. Primary lug kits are included with transformers rated 112.5 KVA, 150° C rise. Consult factory for lug kits for all other ratings.
2. Screw type lugs suitable for aluminum or copper conductor.
- \* 3. Catalog numbers 50403, 50404, and 50405 to be used only on transformers with one primary and one secondary (two windings total) and at least one delta winding. Also, one winding must have a voltage of 480V or above while the other winding must have a voltage of 208V or above or be 240 Delta with a 120 lighting tap (high-leg). For example, voltages of 480-208Y/120 and 480-240/120LT are acceptable connections for these lugs.

## Weather Shield Kits

Catalog Number	Overhang Extension (2 top & 2 bottom)	Approximate Weight in Pounds	Catalog Number	Overhang Extension (2 top & 2 bottom)	Approximate Weight in Pounds
WS-2	2 - 1/16 inches each side	10	WS-10A	2 - 1/16 inches each side	16
WS-3	2 - 1/16 inches each side	10	WS-10B	2 - 1/16 inches each side	16
WS-4	2 - 1/16 inches each side	15	WS-12	2 - 1/16 inches each side	22
WS-5	2 - 1/16 inches each side	15	WS-12A	2 - 1/16 inches each side	20
WS-6	2 - 1/16 inches each side	16	WS-14	2 - 1/16 inches each side	28
WS-7	2 - 1/16 inches each side	16	WS-16	2 - 1/16 inches each side	35
WS-8	2 - 1/16 inches each side	17	WS-18	2 - 1/16 inches each side	15
WS-9	2 - 1/16 inches each side	18	WS-18A	2 - 1/16 inches each side	12
WS-10	2 - 1/16 inches each side	20			

**WEATHERSHIELD NOTE:** Weathershield catalog numbers are listed in the technical data sections for each product. Addition of a weathershield kit converts the transformer from NEMA 2 to NEMA 3R - UL® listed product.

## Wall Mount Brackets

Catalog Number	Type	Approximate Weight in Pounds	Use With . . .
WMB-3	Indoor/Outdoor	24	Wall mount bracket catalog numbers are listed in technical data sections for each product.
WMB-4	Indoor/Outdoor	60	

## Primary Fuse Kit

Catalog Number	Approximate Weight in Pounds	Use With . . .
FPFK-1	1	Industrial Control Transformers